

NFPA 70E COMPLIANCE GUIDE

This guide shall only be used in conjunction with performing the necessary calculations contained in a flash hazard analysis to determine the proper cal/cm². If the results of the calculations exceed the cal/cm² that correspond to the HRC found on this guide, you must use clothing that complies with the calculation.

Panelboards Rated 240 V and Below - Notes 1 and 3				600 V Class Switchgear (with power circuit breakers or fused switches) - Notes 5 and 6				NEMA E2 (fused contactor) Motor Starters, 2.3 kV through 7.2 kV			
TASK (equipment is energized & work is done within the flash protection boundary)	V-Rated Gloves	V-Rated Tools	HRC	TASK (equipment is energized & work is done within the flash protection boundary)	V-Rated Gloves	V-Rated Tools	HRC	TASK (equipment is energized & work is done within the flash protection boundary)	V-Rated Gloves	V-Rated Tools	HRC
Circuit Breaker (CB) or fused switch operation with covers on			0	CB or fused switch operation with enclosure doors closed			0	Contactor operation with enclosure doors closed			0
CB or fused switch operation with covers off			0	Reading a panel meter while operating a meter switch			0	Reading a panel meter while operating a meter switch			0
Opening hinged covers (to expose bare, energized parts)			0	Work on control circuits with energized parts 120 V or below, exposed	Y	Y	0	Work on control circuits with energized parts 120 V or below, exposed	Y	Y	0
Removal of bolted covers (to expose bare, energized parts)			1	CB or fused switch operation with enclosure doors open			1	Insertion or removal (racking) of starters from cubicles, doors closed			2
Remove or Install CB's or fused switches	Y	Y	1	Insertion or removal (racking) of CB's from cubicles, doors closed			2	Contactor operation with enclosure doors open			2
Work on energized parts, including voltage testing	Y	Y	1	Opening hinged covers (to expose bare, energized parts)			2	Insertion or removal (racking) of starters from cubicles, doors open			3
Panelboards / Switchboards Rated 240 V to 600 V (with molded case or insulated case CB's) - Notes 1 & 3				Other 600 V Class (277 V to 600 V, nominal) Equipment - Lighting or small power transformers (600V Max) - Note 3				Metal Clad Switchgear, 1 kV and Above			
TASK (equipment is energized & work is done within the flash protection boundary)	V-Rated Gloves	V-Rated Tools	HRC	TASK (equipment is energized & work is done within the flash protection boundary)	V-Rated Gloves	V-Rated Tools	HRC	TASK (equipment is energized & work is done within the flash protection boundary)	V-Rated Gloves	V-Rated Tools	HRC
CB or fused switch operation with covers on			0	Opening hinged covers (to expose bare, energized parts)			1	Reading a panel meter while operating a meter switch			0
CB or fused switch operation with covers off			1	Removal of bolted covers (to expose bare, energized parts)			2	CB or fused switch operation with enclosure doors closed			2
Work on energized parts, including voltage testing	Y	Y	2	Application of safety grounds, after voltage test	Y		2	Work on control circuits with energized parts 120 V or below, exposed	Y	Y	2
600 V Class Motor Control Centers (MCC's) - Notes 2 (except as indicated) and 3				Other 600 V Class (277 V to 600 V Nom.) Equip - Revenue meters (kWH at primary voltage & current) - Note 3				Other Equipment 1 kV and Above - Metal clad load interrupter switches, fused or unfused			
TASK (equipment is energized & work is done within the flash protection boundary)	V-Rated Gloves	V-Rated Tools	HRC	TASK (equipment is energized & work is done within the flash protection boundary)	V-Rated Gloves	V-Rated Tools	HRC	TASK (equipment is energized & work is done within the flash protection boundary)	V-Rated Gloves	V-Rated Tools	HRC
CB or fused switch or starter operation with enclosure doors closed			0	Cable trough or tray cover removal or installation			1	Switch operation, doors closed			2
Reading a panel meter while operating a meter switch			0	Miscellaneous equipment cover removal or installation			1	Outdoor disconnect switch operation (gang-operated, from grade)			2
Work on control circuits with energized parts 120 V or below, exposed	Y	Y	0	Application of safety grounds, after voltage test	Y		2	Insulated cable exam, in open area	Y		2
CB or fused switch or starter operation with enclosure doors open			1	Insertion or removal	Y		2	Opening hinged covers (to expose bare, energized parts)			3
Opening hinged covers (to expose bare, energized parts)			1	Work on energized parts, including voltage testing	Y	Y	2	Outdoor disconnect switch operation (hookstick operated)	Y	Y	3
Removal of bolted covers (to expose bare, energized parts)			2					Removal of bolted covers (to expose bare, energized parts)			4
Application of safety grounds, after voltage test	Y		2					Insulated cable examination, in manhole or other confined space	Y		4
Work on energized parts, including voltage testing	Y	Y	2					Work on energized parts, including voltage testing	Y	Y	4
Work on control circuits with energized parts >120 V exposed	Y	Y	2					Work on control circuits with energized parts >120 V exposed	Y	Y	4
Insertion or removal of individual starter "buckets" from MCC - Note 4	Y		3								

Minimum Clothing Requirements

HRC	Protective Clothing	Minimum Cal/cm ²	PPE (Safety glasses, hearing protection, leather safety shoes required for all)
0	Natural fiber long-sleeved shirt and pants	N/A	
1	FR Long-sleeved shirt and pants or FR coveralls	4	Hard Hat, Arc-Rated Face Shield
2	FR Long-sleeved shirt and pants or FR coveralls	8	Hard Hat, Arc-Rated Face Shield and 8cal/cm2+ Stocking Hood or Multi-Layer Switching Hood
3	Natural fiber short sleeved shirt and long pants and Arc Rated (25 cal) Arc Flash Suite Jacket and Bib Overalls / Coveralls / 50" Coat with Leggings with Switching Hood	25	Hard Hat, Multi-Layer Switching Hood
4	Natural fiber short sleeved shirt and long pants and Arc Rated (40 cal) Arc Flash Suite Jacket and Bib Overalls / Coveralls / 50" Coat with Leggings with Switching Hood	40	Hard Hat, Multi-Layer Switching Hood

* If the notes cannot be satisfied, work must be performed de-energized.

- Note 1 Maximum of 25 kA short circuit current available, 0.03 second (2 cycle) fault clearing time.
 Note 2 Maximum of 65 kA short circuit current available, 0.03 second (2 cycle) fault clearing time.
 Note 3 For < 10 kA short circuit current available, the HRC required may be reduced by one category.
 Note 4 Maximum of 42 kA short circuit current available, 0.33 second (20 cycle) fault clearing time.
 Note 5 Maximum of 35 kA short circuit current available, ≤ 0.5 second (30 cycle) fault clearing time.
 Note 6 For < 25 kA short circuit current available, the HRC required may be reduced by one category.
 *Circuits over 40cal/cm² should only be worked de-energized.

Revised 8-05

Definitions: Y=Yes (Required)

V-Rated Gloves : gloves rated and tested for the maximum line-to-line voltage upon which work will be done. Leather protectors must be worn externally if v-rated rubber gloves could be damaged.

V-Rated Tools : tools rated and tested for the maximum line-to-line voltage upon which work will be done.

HRC : Hazard Risk Category

FR : Flame Resistant